



Sunmi Blink

QR code reader

LED/Buzzer reminder
45° angle for scanning
Individual customization



Aluminum
border



Scan



Mobile
Payment

Size	97mm x 90mm x 100mm
Scanning window	75mm x 75mm
Input	5V ± 0.5V
Output	> 190mA
Sleep current	> 1mA
Sensor	300 thousand pixels
Recognition precision	QR code > 10mil
Maximum frame	30FPS
CODE type	QR Code/CODE 128
Port	USB Type-A (1.5m)
Reminder	LED/Buzzer
Operating temperature	-10°C ~ 55°C
Storage temperature	-40°C ~ 70°C
Operating humidity	5% ~ 95% (NO condensation)
Operating system	Windows /Android/Linux

Note:

1. Real memory will be reduced due to a number of factors, and there are differences. Operating system also occupy part of memory.
2. Actual product specifications when sold take precedence over what may be listed at this catalogue; Any changes may be made without prior notification